A New Approach To Accelerometer-based Head Tracking for Augmented Reality & Other Applications

M. S. Keir^{1,2}, C. E. Hann¹, J. G. Chase¹, and X. Q. Chen¹

¹Department of Mechanical Engineering

²Human Interface Technology Lab NZ
University of Canterbury

Presented by Matthew Keir

Introduction

- Motivation
- The Inverted Pendulum Model
 - Difficulties in solving the model equations
 - A feasible method to solving the model equations
- Experimental Setup
- Results
 - Model Verification
 - Robustness to Noise
 - Dynamic Performance
 - Real Results, and Improved Results
- Conclusions and Future work

Motivation

- Accurate head tracking is required for compelling Augmented Reality Interfaces
- There are many different tracking technologies applied to this problem. However, none are yet proven in a highly dynamic environment.

InertiaCube2: InterSense

3D-Bird: Ascension

3DM-G: MicroStrain

Key Objective

**To improve dynamic accuracy of
viewpoint tracking for Augmented
Reality.**

The Inverted Pendulum Model

Model Equations

$$A_T = (R/g)\ddot{\theta} - \sin(\theta)$$

$$A_R = (R/g)\dot{\theta}^2 - \cos(\theta)$$

General Engineering Approach

- Numerically Solving the Tangential Equation
 - Using the true Initial Conditions

The Linear Tangential Equation

$$A_T = (R/g)\ddot{\theta} - \theta$$

$$\theta = \boxed{C_2 e^{\frac{\sqrt{g}}{\sqrt{R}} t}} + C_1 e^{-\frac{\sqrt{g}}{\sqrt{R}} t} - A_T$$

- A small error of $1e^{-18}$, applied to the angular velocity IC destabilises the solution and illustrates the ill conditioning present in this problem.

Feasible Solution Method

Choosing the correct solution

Experimental Setup

Inverted Pendulum Apparatus

Accelerometer

Pendulum

Optical Encoder

Fixed Cart

Accelerometer Calibration

Capture Equipment

Results: Model Verification

- The tangential equation is verified in terms of acceleration and angle.

Results: Robustness to Noise

Error Response to the Presence of Noise

Mean Absolute Noise	Mean Error (deg)	Standard Deviation (deg)
None (0mg)	0.0001	0.0002
Medium (3.3mg)	0.34	0.31
<i>Medium Shifted</i>	<i>0.27</i>	<i>0.16</i>
Maximum (8.3mg)	0.52	0.45

Shifting the accelerometer improves the radial acceleration signal

Results: Dynamic Performance

- Stable dynamic performance is achieved in the region of interest.

Results: Real Results

Error Results for Experimental Data

Theta Error	Real Data
Mean (deg)	0.39
Standard Deviation (deg)	0.33

Improved Method

- The improved method allows more data to be used without compromising the linearization of $\sin(\theta)$ term in the DE. Thus a better fit is achieved reducing the variability in C1 and C2 and in the final result.

Results: Improved Method

Experimental Error Results

Data	Max (deg)	STD (deg)	Mean (deg)	%
A ($\approx 0.75\text{Hz}$)	1.7	0.40	0.61	4.25
B ($\approx 1\text{Hz}$)	0.91	0.23	0.27	5.23
C (random)	3.5	0.65	0.92	—

Conclusions and Future Work

- This work achieves dynamic orientation tracking for a single degree of rotation in the vertical plane using only a dual axis accelerometer.
- Future work includes:
 - comparing results to other available devices.
 - introducing other linear motions, a second accelerometer?
 - human testing and comparison with an infra red optical tracking system.

Acknowledgments

- Co-authors...

Dr Christopher E Hann

Professor Geoffrey Chase

Associate Professor Xiaoqi Chen

- Technical Help

Rodney Elliott